

GP338 PORTABLE RADIO - A VERSATILE RADIO

KEY FEATURES AND BENEFITS

X-PAND™ Audio Technology:

Motorola's special voice compression and expansion technology called X-PAND™ enables crisper, clearer and stronger audio quality, allowing you to keep communicating, even in any noisy environment.

128 Channels

Maximum of 128 channels to organise work groups with ease and efficiency.

14-Character Alpha Numeric Dot Matrix Display:

Clear and easy to read text display.

Battery Strength Indicator:

Easy-to-read on-screen LCD display indicator alerting user on battery strength.

Name & Tone Tagging:

Capability to assign up to 8 unique ring tones to different users/talkgroups, and the visual caller ID display makes caller identification possible.

Received Signal Strength Indicator:

A very user-friendly feature to display radio signal strength in the vicinity where you operate in.

Clock and Reminder Alarm:

Set time stamp on incoming recorded messages; Or, set the alarm to remind user of important appointments.

Emergency Siren:

Easy-to-access, one-touch button with piercing alarm to seek help in critical situations.

6 Programmable Buttons

Quick and easy access to most frequently used features.

Adjustable RF Power Levels

Optimised coverage and conserve battery consumption.

Internal Voice Operated Transmissions (VOX)

For hands-free operation, activate this option by speaking with the optional headsets.

Repeater/Talkaround

Freedom to communicate via a repeater for wide area coverage; or bypass a repeater and talk directly to another unit for easy local unit-to-unit communications.

Field Retrofit Option Boards:

Easy to install, affordable add-on functionality whenever your needs arise.

Option Boards are available for:

- DTMF Decode for in-coming calls capability.
- Voice Storage for recording and playing back voice messages.
- III) Mandown Alert for triggering an emergency procedure when the radio is horizontal or still for a pre-defined time. Ideal for radio users who work alone or in isolated environments.



Flexible with Good Audio Quality

Performs Under Any Condition:

The GP338 is essential for growing organisations because of its unique versatility. When necessary, the radio can easily be programmed in the field to add or delete features. So, whether it's the harsh environment of a construction site or the posh elegance of an exclusive hotel, the radio of choice is the GP338. It's the radio that grows with you.

Ideal when you need:

- To communicate frequently with multiple work groups.
- A rugged radio to perform under harsh outdoor condition
- To communicate in a high-noise environment
- To coordinate law enforcement and emergency
- Constant up-to-the-minute information.

Enhance Your Radio's Capabilities

A comprehensive range of accessories is available so that the radios can be customised to suit your needs. Adding the proper headsets, microphones, batteries, chargers or carry cases can enhance the productivity of the people who use two-way radios. Motorola accessories are built with the highest quality standards and are specially engineered to assure maximum performance of your radio, no matter what profession you're in.



ight Weight Head Set



NiMH Battery & Belt Clip



Nylon Carry Case



Multi-unit Charger



impres™ Smart Energy System



Remote Speaker Microphone PMMN4002

ENHANCED SIGNALLING FEATURES:

The GP338 two-way radio supports these three signalling protocols:

I) MDC1200 Signalling

- PTT-ID (Encode/Decode)
- Identify your outgoing calls and incoming callers
- Voice Selective Call (Encode/Decode)
- Send and receive a call from a specific group or individual
- Selective Radio Inhibit (Decode)
 - Allows system owner to disable stolen or missing radios
- Status/Messages (Encode)
 - Pre-defined text messages can be assigned to enable users to send frequently used messages and statuses quickly, without the need to talk
- Call Alert (Encode/Decode)
 - Inform unavailable users that you're trying to reach them, and receive alerts of incoming calls when you're a short distance away from your radio
- Radio Check (Encode/Decode)
 - Check whether another user's radio is activated, and let others check your radio status
- Emergency (Encode)
 - Sounds an alarm or alerts dispatcher in urgent situations

II) Quik Call II Signalling

- Call Alert (Encode/Decode)
- Voice Selective Call (Encode/Decode)

III) Dual Tone Multiple Frequency (DTMF) Signalling

Other GP338 Features:

- Channel Scan
- Time-Out-Timer
- PL/DPL
- Busy Channel Lockout

ACCESSORIES SOLUTION

Battery Options:

Flexible choice of batteries:

- NiCD Battery
- · High Capacity NiMH Battery
- Ultra High Capacity NiMH Battery
- Factory Mutual Approved NiCD & NiMH Batteries
- Lithium Ion Battery

Powerful impres™

Smart Energy Solution

The impres™ Smart Energy System helps battery maintenance, predicts end-of-service life and provides real-time battery usage information.

GP338 Specifications

| N | | |
|---|--|--|
| | | |

| *Frequency (MHz): | 29-42 / 35-50 / 136-174 / 330-400 / 403-470 / 450-527 |
|-------------------|---|
| Channel Capacity: | 128 Channels |
| Power Supply: | Provided through rechargeable battery - 7.5V |

| | , | | | | |
|---|--|--|--|--|--|
| DIMENSIONS: | H x W x D | | | | |
| With Standard High Capacity NiMH Battery: | 137mm x 57.5mm x 37.5mm | | | | |
| With Ultra High Capacity NiMH Battery: | 137mm x 57.5mm x 40.0mm | | | | |
| With NiCD Battery: | 137mm x 57.5mm x 40.0mm | | | | |
| With Lilon Battery: | 137mm x 57.5mm x 33.0mm | | | | |
| | (Radio footprint height excluding knobs) | | | | |
| WEIGHT: | | | | | |
| With Standard High Capacity NiMH Battery: | 428 gm | | | | |
| With Ultra High Capacity NiMH Battery: | 508 gm | | | | |
| With NiCD Battery: | 458 gm | | | | |
| With Lilon Battery: | 358 gm | | | | |
| | | | | | |

| AVERAGE BATTERY LIFE @ 5/5/90 CYCLE | Low Power | High Power | |
|---|--|---|--|
| With Standard High Capacity NiMH Battery: | 11 hours | 8 hours | |
| With Ultra High Capacity NiMH Battery: | 14 hours | 11 hours | |
| With NiCD Battery: | 12 hours | 9 hours | |
| With Lilon Battery: | 11 hours | 8 hours | |
| Sealing: | Withstands rain te | esting per MIL STD 810 C/D/E and IP54 | |
| Shock and Vibration: | Protection provided via impact resistant housing exceeding | | |
| | MIL STD 810-C/D/E and TIA/EIA 603 | | |
| Dust and Humidity: | Protection provide | d via environment resistant housing exceeding | |
| | | | |

MIL STD 810 C/D/E and TIA/EIA603

| TRANSMITTER | | | RECEIVER | | |
|--------------------------------|----------------------|---------------------|------------------------------|---------------------|--------------------------|
| SPECIFICATION | Low Band | VHF/UHF | SPECIFICATION | Low Band | VHF/UHF |
| *Frequency (MHz) | 29 - 42, 35 - 42 | 136-174 / 330-400 / | *Frequency (MHz) | 29 - 42, 35 - 42 | 136-174 / 330-400 / |
| | | 403-470 / 450-527 | | | 403-470 / 450-527 |
| Frequency separation | Full bandsplit# | | Frequency separation | Full bandsplit# | |
| Channel spacing | 12.5 / 20 / 25kHz | | Sensitivity (12dB SINAD) EIA | .30μV | .25µV |
| Freq Stability: | | | Intermodulation (EIA) | 65dB | 70dB |
| (-30oC to 60oC,+25oC Ref.) | ± 0.0010% | +/- 0.00025% | Adjacent Channel Selectivity | 60dB @12.5, | 60dB @ 12.5kHz, |
| Power | 6W | 5W (VHF) | | 70dB @ 25kHz | 70dB @ 25kHz |
| | | 4W (UHF) | Spurious Rejection | 70dB | |
| Modulation limiting | ±2.5 @ 12.5kHz, ±4.0 |) @ 20kHhz, | Rated Audio | 500 mW | |
| | ±5.0 @ 25kHz | | Audio Distortion | 3% | |
| FM Hum & Noise | 40dB | | Hum and Noise | -45dB @ 12.5kHz, -5 | 50dB @ 25kHz |
| Conducted/Radiated Emission | 36 dBm < 1 GHz / | | Audio Response (300-3000Hz) | +1 to -3dB | |
| | 30 dBm > 1 GHz | | Conducted Spurious Emission | -57dBm < 1Ghz, -47 | dBm > 1Ghz / FCC Part 15 |
| Modulation FCC Type | 12.5 kHz 11K0 F3E / | 25 kHz 16K0F3E | | | |
| Audio Response | | | | | |
| (from 6 dB/octave pre-emphasis | 300-3000Hz) | | | | |
| | +1 to -3dB | | | | |
| Audio Distortion | 3% | | | | |

Availability subject to country law and regulations. Radios meet applicable regulatory requirements. Specifications subject to change without notice. Specifications are not representative of all radios and may vary in different radios.

Not applicable to Low Band

Portable Military Standards 810 C, D, & E

| | 810 C | | 810 D | | 810 E | |
|--------------------|---------|------------|---------|------------|---------|------------|
| Applicable MIL-STD | Methods | Procedures | Methods | Procedures | Methods | Procedures |
| Low Pressure | 500.1 | 1 | 500.2 | 2 | 500.3 | 2 |
| High Temp | 501.1 | 1, 2 | 501.2 | 1, 2 | 501.3 | 1, 2 |
| Low Temp | 502.1 | 1 | 502.2 | 1, 2 | 502.3 | 1, 2 |
| Temp. Shock | 503.1 | 1 | 503.2 | 1 | 503.3 | 1 |
| Solar Radiation | 505.1 | 1 | 505.2 | 1 | 505.3 | 1 |
| Rain | 506.1 | 1, 2 | 506.2 | 1, 2 | 506.3 | 1, 2 |
| Humidity | 507.1 | 2 | 507.2 | 2, 3 | 507.3 | 2, 3 |
| Salt Fog | 509.1 | 1 | 509.2 | 1 | 509.3 | 1 |
| Dust | 510.1 | 1 | 510.2 | 1 | 510.3 | 1 |
| Vibration | 514.2 | 8, 10 | 514.3 | 1 | 514.4 | 1 |
| Shock | 516.2 | 1, 2, 5 | 516.3 | 1, 4 | 516.4 | 1, 4 |

Factory Mutual Approval

GP338 radio units are certified by Factory Mutual Approvals as intrinsically safe for use in Division 1, Class I, II, III, Groups C,D,E,F,G and Division 2, Class I, Groups A,B,C,D, when ordered with the Factory Mutual approved battery option.

Motorola: Reliability & Quality



ACCELERATED LIFE TESTING

Stringent Motorola Accelerated Life Testing simulating five years of hard use in real life. EIA R5-3168 in Shock, Vibration, Dust, Humidity, IP54 for Sealing.



MIL-STD 810C. D AND E

Stamp of approval from the U.S.
Military for use in rough environments.



ISO 9001 STANDARD

Compliance with ISO 9001 Standard - on international quality system assurance on design, development, production, installation and servicing of a product.



